

# SmokeESC RCP-3000 Remote Control Panel

## Device description

The RCP-3000 is a remote control panel for use in the SmokeESC system. The RCP-3000 allows you to monitor, activate and block the state of one CAB-3000 board. Thanks to the built-in ignition switch, it provides protection against unauthorized access. A clear and easy-to-use interface enables quick reaction when the situation requires it.

## Features

### Easy-to-use

A clear and easy-to-use interface enables quick response in case of fire and convenient tests during commissioning and inspection. Large indicator lights inform about the status of the connected board.

### Protection against unauthorized access

Thanks to the built-in ignition switch, it protects against unauthorized access and at the same time allows for quick start-up.

### Convenient connection

Plenty of space in the housing. Multiple cable glands allow for quick and convenient installation.

## Technical parameters

PARAMETER	VALUE
Supply voltage	24 V DC
Power consumption	typ. 15 mA, $I_{MAX} < 65$ mA
Operating temperature	from -25 °C to +50 °C
Enclosure protection rating	IP54
Dimensions	205x132x70 mm
Weight	500 g

